

Update: 01/2024

 ACCIAIO INOX AISI 316L STAINLESS STEEL AISI 316L EDELSTAHL AISI 316L		 15-108
 Germany	  **	
 France	 	
 Austria	 *	
 Norway	  *	
 Sweden		
 Netherlands		
 Switzerland		
 Denmark	  *	
 Russia		
 Italy	 	
 Czech Rep.	 *  AO 216 Fire Testing	
 Australia	  *	
 Poland	   *	
 USA		

 ACCIAIO INOX GAS AISI 316L STAINLESS STEEL GAS AISI 316L EDELSTAHL GAS AISI 316L	
 Germany	
 Austria	 *
 ACCIAIO AL CARBONIO CARBON STEEL C-STAHl	
 Germany	 **
 France	 *
 Sweden	
 Czech Rep.	 *  AO 216 Fire Testing
 Poland	  *
 Australia	 *

* Omologazione ottenuta direttamente dal distributore.


Approval obtained directly by our distributor.

Inhaber der Zulassung ist unser Vertreter.

** Gamma omologata **VdS** da Ø22 a Ø108 mm, valida esclusivamente per l'utilizzo abbinato di tubi e raccordi Eurotubi Europa.

VdS approved range from Ø22 to Ø108 mm, valid only for the combined use of Eurotubi Europa pipes and fittings.


VdS zugelassen von Ø22 - 108 mm, gilt ausschliesslich bei Verwendung von Eurotubi Fittings kombiniert mit Eurotubi Europa Rohren.



Manicotto misto - filetto femmina

Adaptor with female thread

Übergangsmuffe I.G.




Code	d - Rp	L	Z			MOQ
C80NB-LBP	12-Rp ^{3/8}	33	5	50	20	120
C80PB-LBP	12-Rp ^{1/2}	38	8	50	20	120
C80NC-LBP	15-Rp ^{3/8}	35	4	56	20	100
C80PC-LBP	15-Rp ^{1/2}	37	4	46	20	200
C80QC-LBP	15-Rp ^{3/4}	42	8	75	20	100
C80PD-LBP	18-Rp ^{1/2}	37	4	64	20	160
C80QD-LBP	18-Rp ^{3/4}	38	4	87	20	160
C80PE-LBP	22-Rp ^{1/2}	37	2	90	20	160
C80QE-LBP	22-Rp ^{3/4}	40	4	95	20	200
C80RE-LBP	22-Rp1	43	4	119	20	120
C80PF-LBP	28-Rp ^{1/2}	44	8	150	10	120
C80QF-LBP	28-Rp ^{3/4}	39	2	138	10	120
C80RF-LBP	28-Rp1	44	4	110	10	200
C80RG-LBP	35-Rp1	50	8	248	10	80
C80SG-LBP	35-Rp1 ^{1/4}	50	7	240	10	120
C80TH-LBP	42-Rp1 ^{1/2}	59	10	286	5	100
C80VJ-LBP	54-Rp2	70	11	539	5	80

Manicotto misto - filetto maschio

Adaptor with male thread

Übergangsmuffe A.G.



Code	d - R	L	H			MOQ
C81NB-LBP	12-R ^{3/8}	42	24	53	20	120
C81PB-LBP	12-R ^{1/2}	42	24	67	20	120
C81NC-LBP	15-R ^{3/8}	42	21	42	20	200
C81PC-LBP	15-R ^{1/2}	42	21	53	20	200
C81QC-LBP	15-R ^{3/4}	44	23	82	20	100
C81PD-LBP	18-R ^{1/2}	43	22	65	20	200
C81QD-LBP	18-R ^{3/4}	45	24	86	20	160
C81PE-LBP	22-R ^{1/2}	43	20	71	20	160
C81QE-LBP	22-R ^{3/4}	45	22	80	20	200
C81RE-LBP	22-R1	47	24	147	20	200
C81QF-LBP	28-R ^{3/4}	47	23	96	10	200
C81RF-LBP	28-R1	49	25	111	10	200
C81RG-LBP	35-R1	56	30	162	10	200
C81SG-LBP	35-R1 ^{1/4}	54	28	164	10	200
C81TG-LBP	35-R1 ^{1/2}	54	28	278	10	100
C81TH-LBP	42-R1 ^{1/2}	58	26	206	6	84
C81VJ-LBP	54-R2	73	36	349	4	80
C81XK	76,1-R2 ^{1/2}	124	69	926	1	10
C81YL	88,9-R3	137	74	1.144	1	10
C81ZM	108-R4	159	82	1.889	1	5